

| Typ | | HFT 2 | HFT 3 | HFT 4 | HFT 6 | HFT 8 |
|---|-------|-----------|-----------|-----------|-----------|------------|
| Bestellnummer | | 408 025 | 408 035 | 408 045 | 408 065 | 408 085 |
| EAN- Code 4026187... | | ...196486 | ...210007 | ...210014 | ...210045 | ...210076 |
| | | Verteiler | | | | |
| Frequenzbereich | [MHz] | 5...1218 | | | | |
| Verteildämpfung Eingang-Ausgänge | | | | | | |
| 5 - 376 MHz | [dB] | 3,1 ± 0,2 | 5,0 ± 0,2 | 6,6 ± 0,3 | 8,0 ± 0,3 | 9,9 ± 0,3 |
| 376 - 1218 MHz | [dB] | 3,5 ± 0,5 | 5,6 ± 0,8 | 7,3 ± 0,9 | 8,9 ± 1 | 10,8 ± 1,1 |
| Entkopplung Ausgang-Ausgang (worst case) | | | | | | |
| 5 - 94 MHz | [dB] | 37 | 29 | 30 | 30 | 27 |
| 94 - 188 MHz | [dB] | 39 | 32 | 37 | 35 | 34 |
| 188 - 376 MHz | [dB] | 33 | 31 | 35 | 33 | 31 |
| 376 - 950 MHz | [dB] | 29 | 29 | 30 | 20 | 28 |
| 950 - 1218 MHz | [dB] | 25 | 25 | 28 | 20 | 22 |
| Reflexionsdämpfung Eingang | | | | | | |
| 5 - 94 MHz | [dB] | 27 | 29 | 21 | 22 | 23 |
| 94 - 188 MHz | [dB] | 26 | 31 | 23 | 25 | 26 |
| 188 - 376 MHz | [dB] | 26 | 26 | 23 | 27 | 24 |
| 376 - 950 MHz | [dB] | 23 | 24 | 17 | 13 | 22 |
| 950 - 1218 MHz | [dB] | 21 | 24 | 17 | 13 | 21 |
| Reflexionsdämpfung Ausgang | | | | | | |
| 5 - 94 MHz | [dB] | 27 | 25 | 23 | 23 | 23 |
| 94 - 188 MHz | [dB] | 34 | 30 | 32 | 27 | 31 |
| 188 - 376 MHz | [dB] | 30 | 27 | 25 | 24 | 26 |
| 376 - 752 MHz | [dB] | 25 | 23 | 18 | 18 | 22 |
| 752 - 950 MHz | [dB] | 24 | 21 | 17 | 14 | 20 |
| 950 - 1218 MHz | [dB] | 25 | 18 | 15 | 14 | 18 |