

Typ		GUT 103			
Bestellnummer		540 831			
EAN-Code		4026187410988			
		Stichleitungsdose			
Frequenzbereich					
	[MHz]	5 - 68	87,5 - 108	125 - 862	950 - 2400
Anschlussdämpfung					
Buchse RF	[dB]	-	2 ± 1,5	-	-
Stecker TV		1 ± 1,5	-	2 ± 1,5	-
F-Buchse SAT		-	-	-	2 ± 1,5
Reflexionsdämpfung					
Eingang	[dB]	> 10	> 9	> 5	> 5
Buchse RF		-	> 8	-	-
Stecker TV		> 10	-	> 5	-
F-Buchse SAT		-	-	-	> 5
Entkopplung					
RF - TV	[dB]	> 30	> 17	> 20	-
TV - SAT		> 4 bis 20 MHz	-	> 10	> 9
FM - SAT		> 10 ab 20 MHz	> 25	-	> 30
		-			

maximal 500 mA LNB-Strom über F-Anschluss